

iMIX 2



STEREO TWO-ZONE MIXING PRE-AMPLIFIER

A stereo two-zone mixer preamplifier with digital source selector, volume, tone and balance controls. iMix 2 mixer preamplifier has all the main features necessary for audio installations: input gain control, phantom power on/o, input priority, tone, balance control and RS232 interface for remote control of main functions. With iMIX2 mixer preamplifier it is possible to create 2 stereo zone or 2 mono zone audio systems, with paging possibilities.



Technical Specifications	iMIX 2
Power supply	AC ~ 230 V / 50 Hz
AC power consumption	20 VA
Frequency response	10 Hz - 50 kHz
THD	< 0,01 %
Input impedance	RCA - 20 k Ω (unbalanced) Phoenix - 47 k Ω (balanced)
Input gain	Line -10 dB Mic -50 dB
Outputs	Maximum output level + 15dB, impedance - 10 k Ω
Priority inputs	Input 4
Tone control	Bass $\pm$ 12 dB, Treble $\pm$ 12 dB
HUM & Noise	-87 dB
Crosstalk	-50 dB @ 1 kHz
Dimensions	482 mm $\times$ 200 mm $\times$ 44 mm
Weight	4 kg
Colour	Black (RAL 9017)

iMIX 2

STEREO TWO-ZONE MIXING PRE-AMPLIFIER



Front panel view



Rear panel view

